

This procedure is only for Mark5A systems presently running Debian Etch distribution with a Linux 2.6.18 kernel. Please note that this is for a system with the *Mark5A IO card ONLY*.

To upgrade to the latest Mark5A application and Conduant SDK 8.2 please perform the following on your system.

First, make sure the application Mark5A is not running. If it is, please End5A before proceeding.

As root:

1) With your favorite editor, edit /etc/apt/sources.list, e.g.
vi /etc/apt/sources.list

2) Add the line:
deb <http://evlbi.haystack.mit.edu/debian/> binary/

3) Execute
apt-get update

4) Execute
apt-get remove mark5

- This step uninstalls the mark5a_1.0.3-i386 package. *NOTE mark5 not mark5a. This step overcomes a naming miss-step on our part and will only have to be done one time.

5) Execute
apt-get install mark5a

- This step will install mark5a_1.0.7 AND upgrade the Conduant SDK to 8.2 or package version streamstor_1.1.1 *Please note *mark5a* not **mark5**

6) Reboot the system and verify the new installation by running:
Mark5A -m0